

NON-PROVISIONAL

PATENT APPLICATION

**ACTIVE POWER FILTER FOR ISOLATING
ELECTRICALLY NOISY LOAD FROM LOW NOISE POWER SUPPLY**

Inventor:

Sam Ochi, a citizen of the United States, residing at
19920 Saraglen Court
Saratoga, California 95070

Assignee:

IXYS Corporation
3540 Bassett Street
Santa Clara, CA 95054

09915202-072301

ACTIVE POWER FILTER FOR ISOLATING ELECTRICALLY NOISY LOAD FROM LOW NOISE POWER SUPPLY

CROSS-REFERENCE TO RELATED APPLICATIONS

[01] This application claims priority from U.S. Provisional Application No. 60/220,050, entitled "Active Power Filter Invention", filed July 21, 2000, which is herein incorporated by reference in its entirety for all purposes.

BACKGROUND OF THE INVENTION

1. FIELD OF THE INVENTION

[02] The present invention relates to the field of supplying direct current (DC) power; and specifically, to filtering noise between the power supply and the load driven by the power supply.

2. DISCUSSION OF THE RELATED ART

[03] Figure 1 illustrates a conventional filter for isolating an electrically noisy load from a low noise main power supply source. The conventional circuit illustrated in Figure 1 is used primarily to filter an electrically noisy load 101 such as a switching DC to DC converter, brushless DC motor, switching logic circuit, or another noisy direct current powered circuit from a low noise main power source, V_{IN} . Inductor L1 acts as a passive low pass filter for isolating a low noise main power source, V_{IN} , from noise generated by the noisy load.

[04] The inductance value of inductor L1 is chosen to optimize the noise filtering requirements. In designing the a conventional circuit such as illustrated in Figure 1, care must be exercised in the choice and physical placement of inductor L1 as it may emit magnetic noise interference, and it may be physically large. Magnetic noise interference may undesirably affect the performance of the load device, the power supply, and other unrelated electronic/magnetic devices in the physically nearby area of the system illustrated in Figure 1.

SUMMARY OF THE INVENTION

[05] An object of the present invention is to create an active power filter which behaves like a filter circuit having a large inductor, but without producing magnetic

interference or physically large components as would be produced by a conventional large inductor. The power filter according to the present invention is suitable for use with switching DC to DC converters, brushless DC fans, switching logic circuits, and other noisy loads.

5 [06] According to the present invention, an active power filter includes a feedback resistor and a shunt capacitor, an operational amplifier equivalent subcircuit, and a voltage drop source. The shunt capacitor connects the positive terminals of the low noise power supply and the noisy load to the positive terminal of the operational amplifier equivalent subcircuit. The feed back resistor connects the negative terminal of the noisy load and the output of the operational amplifier equivalent subcircuit to the negative terminal of the shunt capacitor. The voltage drop source connects the negative terminal of the low noise power supply to the negative terminal of the operational amplifier equivalent subcircuit.

10 [07] According to the present invention, the impedance of the active power filter at a minimum noise frequency is carefully designed so as to be large in comparison to an impedance of the noisy load, for example, the impedance of the active power filter is 1000 times the impedance of the noisy load at the minimum noise frequency. The active power filter according to the present invention is equally capable of protecting a low noise load device to a noisy direct current power supply.

15 [08] According to another aspect of the present invention, the operational equivalent subcircuit includes an operational amplifier, first and second resistors, and a transistor. The first resistor connects the positive terminal of the voltage drop source to the negative input terminal of the operational amplifier. The second resistor connects the output of the operational amplifier to the gate of the transistor. The drain of the transistor is coupled to the negative terminal of the noisy load. The source of the transistor is coupled to the negative terminal of the voltage drop source and to the negative terminal of the low noise direct current power supply. The positive input terminal of the operational amplifier forms the positive input terminal of the operational amplifier equivalent subcircuit.

20 [09] In an exemplary embodiment of the active power filter according to the present invention, the operational amplifier equivalent subcircuit further includes, first and second capacitors. The first capacitor connects the output of the operational amplifier to the negative input terminal of the operational amplifier. The second capacitor connects the output of the operational amplifier to the gate of the transistor. In addition, the operational amplifier equivalent subcircuit may contain a third capacitor and a third resistor which are connected in series between the gate of the transistor and the negative terminal of the low

noise direct current power supply. In an exemplary embodiment, the transistor comprises an N-channel enhancement mode MOS field effect transistor.

[10] These and other features, aspects, and advantages of the present invention are more fully described in the Detailed Description of the Invention with reference to the Figures.

BRIEF DESCRIPTION OF THE DRAWINGS

[11] Figure 1 illustrates a conventional filter for isolating an electrically noisy load from a low noise main power supply source.

[12] Figure 2 illustrates an exemplary load noise generated at the power terminals of the noisy load by the noisy load.

[13] Figure 3 illustrates an active power filter according to the present invention for isolating an electrically noisy load from a low noise main power supply source.

[14] Figure 4 illustrates a simplified circuit according to the present invention of the active power filter for isolating an electrically noisy load.

[15] Figure 5 illustrates an equivalent subcircuit for the active inductor circuit according to the present invention for isolating an electrically noisy load.

[16] The Figures are more thoroughly explained in the Detailed Description of the Invention.

DETAILED DESCRIPTION OF THE INVENTION

[17] Figure 2 illustrates an exemplary load noise, ΔV_{OUT} , that the noisy load 101 generates at its power terminals. As an example, the noisy load 101 may be a 10 Amp DC load with 1 Amp AC (alternating current), ΔI_{OUT} , of noise with approximately 1 V PP (peak-to-peak), and with spectral frequency components as low as 20 Hz, such as illustrated in Figure 2. The dynamic load impedance can be expressed as the following Equation 1.

$$[18] \quad Z_{LOAD} = \Delta V_{OUT} / \Delta I_{OUT} \quad (\text{Equation 1})$$

[19] To maintain low noise for the main power source, V_{IN} , the inductor L1 in Figure 1 should be sized with a high impedance relative to the impedance, Z_{LOAD} , of the noisy load 101, such as $Z_{L1} \approx 1000 * Z_{LOAD}$. This will minimize the affects that the noise in Figure 2 has on the low noise power supply V_{IN} . An equivalent resistance, Z_{LOAD} , of the noisy load 101 for the given conditions from Equation 1 is shown below.

$$[20] \quad Z_{LOAD} = (1VPP) / (1Amp) = 1 \text{ Ohm.}$$

[21] An expression for the impedance of inductor L1 in Figure 1 is shown below as Equation 2.

[01] $Z_{L1} = 2\pi * f * L1$ (Equation 2)

[23] Since the minimum noise frequency f_{min} is 20Hz in the example of Figure 2, and since the desired inductor L1 impedance is 1000 Ohms in this example, rearranging Equation 2 to solve for the inductance L1, the following results.

[24] $L1 = 1000 \text{ Ohms} / (2\pi * 20\text{Hz}) \approx 8 \text{ Henrys}$

[25] A practical inductor L1 having this value of 8 Henrys would weigh greater than 10 pounds and would have a significant physical size.

[26] Figure 3 illustrates an active power filter according to the present invention for isolating an electrically noisy load 301 from a low noise main power supply source, V_{IN} .

[27] The active power filter circuit in Figure 3 according to the present invention serves the same function as the conventional one in Figure 1 without the need for an inductor. The components transistor M1, resistor R1, resistor R2, resistor R3, feedback resistor R4, capacitor C1, capacitor C2, capacitor C3, and shunt capacitor C4 with respect to operational amplifier OA1 form an active inductor. The transistor M1 is implemented, for example, by such as an enhancement mode N-channel MOS field effect transistor. The voltage source V_{DROP} serves to provide the necessary headroom for the active circuitry to properly function.

[01] Figure 4 illustrates a simplified circuit according to the present invention of the active power filter for isolating an electrically noisy load. To understand the functioning of the present invention, the components resistor R1, resistor R2, resistor R3, capacitor C1, capacitor C2, capacitor C3, and transistor M1 can be included into an idealized operational amplifier OA as shown in Figure 4, with only shunt capacitor C4 and feedback resistor R4 remaining along with voltage source V_{DROP} , and low noise power supply V_{IN} , from among the circuit elements shown in Figure 3. From Figure 4, a frequency, $f_{VOUT}(-3db)$ is defined, in which the impedance of shunt capacitor C4 is equal in magnitude to the impedance of feedback resistor R4. At $f_{VOUT}(-3db)$, $\frac{1}{2} \Delta V_{OUT}$ is dropped across feedback resistor R4 and the other $\frac{1}{2} \Delta V_{OUT}$ across shunt capacitor C4. In other words, at the frequency $f_{VOUT}(-3db)$, the circuit impedance of the Figure 4 combination of elements seen by the noisy load 401 is equal to the dynamic load impedance of the noisy load 401 itself.

[29] Consequently, the total impedance at this frequency $f_{V_{out}(-3db)}$ seen by low noise power source V_{IN} is $2 \cdot \Delta V_{OUT} / \Delta I_{OUT}$ or 2 times the dynamic load impedance of the noisy load 401. An expression for $f_{V_{out}(-3db)}$ is given below as Equation 3.

$$[30] \quad f_{V_{out}(-3db)} = 1 / (2\pi R_4 \cdot C_4) \quad (\text{Equation 3})$$

[31] An expression for the impedance for an inductor is given below as Equation 4.

$$[32] \quad Z_L = 2\pi f \cdot L \quad (\text{Equation 4})$$

[33] Figure 5 illustrates an equivalent circuit for the active inductor circuit according to the present invention for isolating an electrically noisy load 501. At $f_{V_{out}(-3db)}$, and solving Equation 4 for L , an expression for the equivalent inductor, L_{EQUIV} is given below as Equation 5.

$$[34] \quad L_{EQUIV} = Z_{LEQUIV} / \{2\pi \cdot f_{V_{out}(-3db)}\} \quad (\text{Equation 5})$$

[35] Using the expression for $f_{V_{out}(-3db)}$ from Equation 3, since $Z_{LEQUIV} = Z_{LOAD}$ at this frequency, and using the expression for Z_{LOAD} from Equation 1, Equation 5 simplifies to the following equation 6.

$$[36] \quad L_{EQUIV} = R_4 \cdot C_4 \cdot \Delta V_{OUT} / \Delta I_{OUT} \quad (\text{Equation 6})$$

[37] A circuit showing the use of equivalent inductor L_{EQUIV} is given in Figure 5. Voltage source V_{DROP} can be set to be $I_{OUTDC} \cdot R_{SERIES}$, where I_{OUTDC} is the average DC operating current of the load and R_{SERIES} is the DC resistance of inductor $L1$ such as in Figure 1.

[01] As a comparison, substituting the conventional example requirement of $L1 = 8$ Henrys from Figure 1 into the active power filter according to the present invention, so that $L_{EQUIV} = 8$ Henrys, and $\Delta V_{OUT} = 1$ VPP, $\Delta I_{OUT} = 1$ Amp R.M.S (root mean square) in Figure 5, from Equation 6,

$$[39] \quad L_{EQUIV} = 8H = R_4 \cdot C_4 \cdot 1V / 1A = R_4 \cdot C_4.$$

[40] By selecting $R_4 = 1$ Megaohm, and solving for C_4 , $C_4 = 8$ H / 1 Megaohm = 8 uF.

[41] While the present invention has been described with reference to its exemplary embodiment, that embodiment is offered by way of example, not by way of limitation. Those of ordinary skill in the art will be enabled by this disclosure to add to or modify the embodiments of the present invention in various ways. For example, the nominal resistances, capacitances, inductances, and load and noise characteristics described above are

only exemplary values, and are by no means restrictive. In addition, although the active power filter has been described as protecting a low noise power supply from a noisy load device, it is to be noted that the the active power filter according to the present invention is equally capable of protecting a low noise load device from a noisy power supply.

- 5 Accordingly, those additions and modifications are deemed to lie within the spirit and scope of the present invention, as delineated by the appended claims.

00915202, 072201